
DIN-RAIL DIGITAL DRIVER FOR HIGH PERFORMANCE PRESSURE VALVES


Industrial driv	Industrial driver model:			Ex-proof driver model:		
E-BM-RES	E-BM-RES			E-BM-RES /A		
Industrial valv	ve models:	LIMZO-R	Ex-proof valve	e models:	LIMZA-R	
RZMO-R	RZGO-R	LIRZO-R	RZMA-R	RZGA-R	LIRZA-R	
AGMZO-R	AGRCZO-R	LICZO-R	AGMZA-R	AGRCZA-R	LICZA-R	

IDENTIFICATION





INSTALLATION TOOLS



PROGRAMMING TOOLS - not included



PC SOFTWARE

E-SW-SETUP supports	NP (USB) BC (CANopen) EW (POWERLINK) valves with SP, SF,	IL (IO-Link) BP (PROFIBUS DP) EI (EtherNet/IP) SL alternated p/Q control	PS (Serial) EH (EtherCAT) EP (PROFINET RT/IRT)	IR (Infrared)
REMARK Atos PC software is des	ianed for Windows ha	seed operative eveteme - \	Nindows 10 or later	

PC SOFTWARE DOWNLOAD



RELATED DOCUMENTATION - www.atos.com


FS900	Operating and maintenance information - tech. table	E-MAN-BM-RES	RES - driver operating manual
F***	High performance pressure valves tech. table	E-MAN-S-BC	CANopen protocol programming manual
P005	Mounting surface - tech. table	E-MAN-S-BP	PROFIBUS DP protocol programming manual
GS203	E-BM-RES drivers - tech. table	E-MAN-S-EH	EtherCAT protocol programming manual
GS500	Programming tools - tech. table		
GS510	Fieldbus - tech. table		
K800	Electric and electronic connectors - tech. table		

The purpose of this quickstart guide is show a logical sequence of basic operations. This guide does not cover all details or variants of Atos valves. All operations described in this document should be performed only by qualified personnel. Operations and images could be subject to change without notice. For further information please refer to related documentation.

CONTACT US


Atos spa - Italy - 21018 Sesto Calende www.atos.com


PRODUCTS OVERVIEW




INSTAL	PROGRAMMING	
STEP 1	STEP 2	STEP 3
MECHANICAL	ELECTRICAL	SOFTWARE


STEP 1 MECHANICAL








To extract the connectors: To insert the connectors: 1. push the connector in its slot 1. push lever 2. pull connector



To wire cables in the connectors: 1. insert the cable termination 2. turn screw with a screwdriver




NOTE: max conductor size 2,5 mm² tightening torque 0,4 ÷ 0,6 Nm

NOTE: all connectors are supplied with a mechanical coding. This feature ensures a unique insertion of each connector in the own slot (e.g. connector A can not be inserted into connector slot of B,C,E,F,G,H)

STEP 2 ELECTRICAL


This section considers the different drivers executions, illustrating the multiple variants of the available electrical connections. The electrical connections have to be wired according to the selected driver code



WARNING: a safety fuse is required in series to driver power supply - 2,5 A time lag fuse

2.1 CONNECTORS

Recommended LiYCY shielded cables: 0,5 mm² max 50 m - for logic - 1,5 mm² max 50 m - for power supply and solenoids



		Pressure transducer
	1	VF +24V (power supply 24Vpc)
F	2	TR+ (4 ÷ 20mA)
_	3	NC
	4	AGND (ground for transducer and potentiometer)
	٧	alve signal and potentiometer power supply
	1	+5V_REF (power supply +5Vpc)
F	2	P_INPUT+ (0 ÷ 10Vpc / 4 ÷ 20mA)
•	3	INPUT- (negative reference for P_INPUT+)
	4	-5V_REF (power supply -5Vpc)
		Monitor signals
	1	EARTH
G	2	AGND (ground for P_MONITOR and potentiomete
G	3	NC
	4	P_MONITOR (0 ± 10Vpc / 4 ÷ 20mA)
		Digital inputs
	1	VL0 (power supply 0Vpc for digital input)
н	2	D_IN1 (input 24Vpc)
• •	3	D_IN0 (input 24Vpc)
	4	VL+ (power supply 24Vpc for digital input)

2.2 FIELDBUS CONNECTORS - only for BC, BP, EH

Select fieldbus connectors according to driver code and proceed with wirings operations





	الميمالميما
	BP (DB9 - 9 pin)
1	SHIELD
3	LINE-B Bus line (low)
5	DGND Data line - termination signal zero
-	. EV Tampination at make along

8 LINE-A Bus line (high)

BP



EΗ

	EH (RJ45 - 8 pin)					
1	1 TX+ Transmitter					
2	RX-	Receiver				
3	TX-	Transmitter				
6	6 RX- Receiver					

driver internal circuit


ELECTRICAL WIRING EXAMPLES FOR INDUSTRIAL VALVES - for Ex-Proof valves please refer to relevant tech. tables

REFERENCE INPUT - VOLTAGE

CAN L Bus line (low) CAN_GND Signal zero data line CAN_SHLD Shield 7 CAN H Bus line (high

cabinet side	F connector pin-out	driver internal circuit
0÷10 Vpc		D INDIT. FOR
Ref. ⊕ → Ø	F2	P_INPUT+ 50K
Ref. ——Ø	F3	NPUT- 50K

0÷10 Vpc Ref. ⊕ → ⊘ Ref. ⊕ → ⊘	F2 F3	P_INPUT+ O_INPUT-	50K 50K	4÷20 mA Ref. ⊕ → ⊘ Ref. ⊕ → ⊘	F2 F3	⊘_P_INPUT+ ⊘INPUT-
COMMON MODE				COMMON MODE		
cabinet side	F, G connectors pin-out	driver intern	al circuit	cabinet side	F, G connectors pin-out	driver i
0÷10 Vpc		D MOUT.	501/	4÷20 mA		D INDUT



REFERENCE INPUT - CURRENT


F connector pin-out

DIFFERENTIAL MODE

INPUT-AGND

MONITOR OUTPUT - VOLTAGE			MONITOR OUTPUT - CURRENT			
MONITOR OUTPUT			MONITOR OUTPUT			
cabinet side	G connector pin-out	driver internal circuit	cabinet side	G connector pin-out	driver internal circuit	
0÷10 Vpc Mon.	G4 G2	© P_MONITOR © AGND	4÷20 mA Mon.		P.MONITOR AGND	


SOLENOID		PRESSURE TRANSDUCER - ONLY CURRENT			
01H SINGLE SOLENOID		PRESSURE TRANSDUCER			
valve solenoid side	C connector driver pin-out signals	E-ATR-8 transducer side	E connector pin-out	driver signals	
666 / 2	OOL 0 C1 0 SOL_S1 C2 0 SOL_S1+	connector code ZBE-08 1 TR	Ø E1 Ø E2 4+20mA	⊘ VF +24V ⊘ TR+	




REMARK off-board drivers are factory preset with default parameters, only few programming operations are mandatory for setup the network parameters and the source of reference signals


Driver programming can be performed through E-SW-SETUP software or via fieldbus

3.1 CONNECTION



Complete the electrical installation and power on the driver with 24Vpc






WARNING: drivers USB port is not isolated!

The use of USB isolator adapter is highly recommended for PC protection (see GS500)


Launch the PC software using E-SW-SETUP icon:

• PC software does NOT detect valid connection communication is not established, please follow wizard procedure 4










Communication established, driver is ON-LINE and it is



NOTE: Bluetooth not available for E-BM-RES

3.2 FIELDBUS - Network Management - only for BC, BP, EH

Node, Station Alias, IP Address, Baudrate, etc... can be set through:

1) Machine central unit (master) - please refer to E-MAN-S-** fieldbus protocol programming manual

Δ<u>×</u>

2) E-SW-SETUP software

N-LINE - Manual

• browse to Network Management - Configuration to change below default settings:



- press Memory Store button and press Save User Set button to save new setting into the driver (see 3.5)
- network configuration settings will be applied at next driver power on or pressing the Restart button


NOTE: configuration files are available in MyAtos area - www.atos.com

3.3 REFERENCES - only for BC, BP, EH

The source of reference signals for valves with fieldbus:

- is preset as Analog by factory default
- can be managed through machine control unit by setting the source from Analog to Fieldbus

In Pressure - Reference select Fieldbus



3.4 SMART TUNING - E-SW-SETUP


Smart tuning allows to adjust the valve dynamic response in order to match different performance requirements.

The valve is provided with 3 factory setting for the pressure control:

dynamic fast response time for best dynamic performances (default factory setting)

balanced average response time suitable for major applications

smooth attenuated response time for slow regulation without overshoots



STORE 3.5

Parameters modifications will be stored into driver permanent memory:



WARNING: during valve parameters storing down the solenoid power supply for a shor time. Do not perform any storing commands while the system is working.

3.6 BACK UP

Parameter modifications will be saved into PC memory:

• press Save button to access Computer SW Archive - Setting Files page, Setting File Name pop-up appears

• input a valid name into **Description** field and press **Ok** button

WIZARD REFERENCE - E-SW-SETUP - only for NP

V Voltage Standard

For Monitor output signal configuration browse to page Others - Monitor Output

-10,00 V 🗘

Input Actual Value 0,00 V Max Input

3.7 CONFIGURATION

BIAS AND SCALE All valves Bias setting: supply the input signal equal to 0 bar • relief valves: increase the Bias until the pressure starts to increase, then lightly reduce the Bias just to bring back the pressure lightly over the minimum regulated value • reducing valves: increase the Bias until is reached the minimum desired value of starting pressure Scale setting: supply the max input signal; adjust the Scale to obtain the max regulated pressure RAMPS Ramps setting: select the required ramp configuration and adjust the ramp time to optimize the pressure response according to the system characteristics No Ramp : no ramps selected BiasP positive bias Single Ramp : setup Ramp 1 ScaleP positive scale Double Ramp : setup Ramp 1 and 2

Reference input signal is factory preset according to selected valve code, defaults are 0 ÷ 10 Vpc for standard and 4 ÷ 20 mA for /I option

Input signal can be reconfigured via PC software selecting between voltage and current, browsing to Reference Analog Range page:

REMARK: Voltage Standard or Current 4..20 mA buttons do not act on Monitor output signal configuration!

press Voltage Standard button

Voltage Standard

press Current 4..20 mA button

Current 4..20 mA

to automatically set the analog input signal to voltage

to automatically set the analog input signal to current

Valve vibration or noise

- presence of air in the solenoid; perform air bleeding procedure see tech. table of the connected valve
- $\bullet \ \, \text{dither frequency too low; increase value of the frequency} \text{please refer to E-MAN-BM-RES operating manual} \\$

The valve does not follow the reference signal

- driver is powered off, verify presence of 24 Vdc power supply and the coil(s) connection
- driver is disabled, verify presence of 24 Vdc on enable pin
- flow/pressure values exceeding the valve's performance limits, verify that hydraulic operating conditions are incompliance with the valve's characteristics
- big hysteresis or spool stick-slip, reduce the dither frequency
- the mechanical pressure limiter interferes with the regulation (only AGMZO and AGRCZO with /P option and only LIRZO,
- LICZO, LIMZO sizes 16, 25, 32 and /P option) check the pressure limiter setting
- spool sticking, contact Atos service center
- poppet sticking (only LIRZO, LICZO, LIMZO) contact Atos service center
- missing piloting pressure, verify that the system pressure is compliant with valve's characteristics
- wrong pilot/drain configuration check if the pilot/drain configuration of the valve corresponds to the effective system layout

Pressure instability or vibration

• select PID4 to operate the valve in open loop:

- if the instability still persists, check eventual anomalies in the hydraulic circuit as the presence of air
- if the instability disappears, select an alternative configuration within PID selection 1, 2 or 3 which better matches the application requirements
- if no one of the above selection fulfills the application, tune P I D parameters at E-SW-SETUP software to obtain the desired dynamic response

PC software parameters modifications are lost when driver is switched off

• parameter store operation was not performed, check store procedure - see STEP 3, section 3.5

PC software parameters modifications have no effect on the valve

• driver is OFF LINE, check connection procedure - see STEP 3, section 3.1

After the modifications of PC software parameters the valve does not work properly

- restore valve factory parameters using 'Load Factory Set' button, located in 'Driver Memory Save' window:
- during restore, the current to the solenoid(s) will be temporarily switched to off!
- factory parameters will be applied at next driver restart or after power off-on sequence!
- perform the bias and scale configurations again!

Move arrow on parameter (e.g. Unit) to display the objects dictionary information to access the parameter via fieldbus If present **List**, press to display values accepted by the parameter Current 4..20 mA NOTE: alternatively right click on any parameter

HINT! - Wizard objects dictionary - only for BC, BP, EH

Press CTRL + H on the PC keyboard to open the context help form

TROUBLESHOOTING